StaffAPI - Changing Phone Status

Created by Unknown User (drew.lederman), last modified on 22/02/13



Client request

To notify the server of your phone status, perform an HTTP POST (<u>HTTP POST@wikipedia</u>) request to the following URL:

```
Unknown macro: 'url-panel'
```

POST arguments

Unknown macro: 'http-post-encoding-info'

Argument	Value
sessionid	The unique session identifier sent in the log in response from the server
status	The new status. See VoIP statuses

Server response

A standard server response containing a UTF-8 encoded XML payload in the following format:

Root node

The parent node for the entire XML payload. If you do not locate this node at the top level, it is likely that the server returned an error response. See error codes for further information.

<kayako_staffapi>

Result

<status>...</status>
<error>...</error>

Node name	Value
status	The status of the request. Any value other that 1 indicates an error.
error	The error message returned by the server

Closing root node

The final XML node is simply the end of the original root node, completing the XML document.

</kayako_staffapi>